

GXEWC\$ – Enable/Disable GX Web Content

The GX thin-client includes an algorithm to decide if a field is displayed with a clickable hyperlink (e.g. a text string of the format “www.global3000.co.uk” will be displayed with a clickable hyperlink). The GXEWC\$ routine allows the GX algorithm to be overridden to either force or suppress a hyperlink on a displayed field.

1. Invocation

To enable or display GX Web Content code:

```
CALL GXEWC$ USING mode
```

where mode is a PIC 9(4) COMP, or literal set to either:

```
0   Disable web content on the next field displayed
1   Enable web content on the next field displayed
```

All other values are invalid and will product unpredictable results.

2. STOP Codes and Exception Conditions

The following STOP codes may be generated by GXEWC\$:

STOP code	Description
14330	GXBTT\$ has been called by an application that is not running on GX.

No exception conditions are returned by GXEWC\$.

3. Programming Notes

GXEWC\$ is only available when running on GX. Any attempt to use GXEWC\$ on a non-GX terminal will result in a STOP code. GXEWC\$ is only available with GSM SP-38, or later.

GXEWC\$ only affects the **next** field displayed by GX.

4. Examples

[EXAMPLE REQUIRED]

5. Copy-Books

None.

6. See Also

None.