

## GXRCDS\$ - Send the Current Record-id to GX

The GXRCDS\$ is used by the Speedbase Windows Manager to send the current Record-id to GX. The Record-id is displayed, together with other information, by the GX Help/About/Application option.

### 1. Invocation

To send the Current Record-id to GX code:

```
CALL GXRCDS$ USING id
```

where *id* is a PIC X(2) field that contains the Record-ID.

### 2. STOP Codes and Exception Conditions

The following STOP codes may be generated by GXRCDS\$:

STOP code	Description
23926	GXRCDS\$ has been called by an application that is not running on GX.
23927	String too large for internal buffer
23928	An attempt was made to call GXSBM\$ on an incompatible version of GX. The version of GX must be V2.7, or later.
23929	An unexpected error has been reported by GX

The following EXIT codes may be returned by GXRCDS\$:

EXIT code	\$\$COND	Description
23922	22	Unable to allocate memory for temporary work buffer

### 3. Programming Notes

GXRCDS\$ is only available with GSM SP-19, and later. GXRCDS\$ is only available when running on GX. Any attempt to use GXRCDS\$ on a non-GX terminal will result in a STOP code.

### 4. Examples

[EXAMPLE REQUIRED]

### 5. Copy-Books

None.

### 6. See Also

None.